



KeyMix 6

The KeyMix 6 is a uniquely flexible, compact and great-sounding mixer offering nine inputs, six channels (three stereo, three mono), a mic preamp, an insert loop plus monitor and main outputs. Its potential applications include:

- Compact onstage mixer for keyboard players, electronic drummers, solo artists etc.
- Input expansion for existing consoles or submixer
- Perfect addition for computer-based music production systems as mic preamp and/or for expanders, drum boxes and samplers
- Space-saving alternative to conventional consoles for restaurants and bars with multiple zones or for exhibitions, seminars etc.

The KeyMix 6 is built in Germany and features SPL-typical build and audio quality at an entry-level price, including:

- Internal power supply, ground lift switch
- Highest quality potentiometers and switches from ALPS
- Double-sided PCB for maximum durability and reliability
- Rugged metal casing

Key Features

- Mic channel with high-quality preamp and 48 V phantom power for condenser microphones
- Two mono inputs (one for low-level signals or microphone) with gain and pan controls
- Three stereo line inputs with dual 1/4" connectors
- Dedicated post-preamp mic channel insert loop for external processors
- Master insert loop for stereo sum processors (e. g. Vitalizer®)
- Channels 1 and 2 can be routed only to monitor outputs
- Separate main and monitor stereo outputs

Technical Specifications

Frequency response:	10 Hz-100 kHz (-0.5 dB)
THD+N:	→90 dB
Noise:	→90 dB
CMRR:	→80 dB
Output resistance:	50 Ohm
Fuse:	125 mA
Dimensions:	19 inch, 1 U rack space

